

Download Tool User Manual

Vision 5.00.05

Content

CONTENT	2
1 OVERVIEW	1
2 HARDWARE INSTALLATION	1
2.1 HARDWARE REQUIREMENT.....	1
2.2 HARDWARE INSTALL.....	1
3 SOFTWARE INSTALLATION.....	3
3.1 SOFTWARE REQUIREMENT.....	3
3.2 SOFTWARE SETTING.....	3
3.2.1 <i>PASSWORD SETTING</i>	3
3.2.2 <i>PORT SETTING</i>	4
3.2.3 <i>DOWNLOAD INFO SETTING</i>	4
3.2.4 <i>CHIP SETTING</i>	6
3.2.5 <i>FLAG SETTING</i>	7
3.2.6 <i>SN SETTING</i>	7
4 RUN THE DOWNLOAD TOOL.....	9
4.1 RUN THE DOWNLOAD TOOL.....	9
4.2 START DOWNLOADING.....	9
4.3 CONNECT TO THE CELLULAR PHONE.....	10
4.4 DOWNLOAD THE LOD FILE.....	10
4.5 UNPLUG THE CELLULAR PHONE.....	11
5 TROUBLESHOOTING	12

1 Overview

The document introduces the basic functions and the usage of the download tool, including the hardware install, the software install, troubleshooting etc. The Download tool is mainly used for the production line. It can be used to download the data to mobile phones including the boot code, the user data etc. Besides, it can erase the data in the flash, such as the user data, the calibration data and the factory data. And we can write a phone SN or a main board SN at the same time when we download the data to our mobile phone. This software is easy to use, and it is very convenient.

2 Hardware installation

2.1 Hardware requirement

1. PC with PCI slot.
2. MOXA CARD with 1-8 port Cable, or USB hub with 8 ports.
supporting the baud of 921600 bps.
3. The fixture for downloading.
4. DC power supply.

2.2 Hardware install

The download tool supports downloading with 8 ports at the same time. The mode of the connection is shown as the figure 1.




Figure 1

If you use the MOXA CARD to download. Insert the MOXA Card into a free PCI slot, and connect the 1-8 ports cable, Then install the MOXA driver .After those steps completed, you will see in the equipments manager shown as the figure 2. It means that the installation completes successfully. Then change the baud rate of all the MOXA Communication port to 921600 as shown in the figure 3.

If you select USB hub to download, You need only connect the appropriate line to the USB hub, and configure the serial ports mapped from the USB device same as the MOXA card.




Figure 2




Figure 3

Attention: Before installing the MOXA card driver, you can adjust the COM setup by the equipments manager. In other words, you can set the origin ports into COM21 & COM22 as shown in the figure 3. Thus, after installing the driver of MOXA, the 8 ports of MOXA to be used follow the 1-8 sequence. It is easy to identify. Certainly, the customer can also perform the above steps in case of 16 ports.

3 Software installation

3.1 Software requirement

Windows 2k or Windows xp; download tool

3.2 Software setting

Some crucial setting work is needed before using the download tool, such as port setting, download info setting, flash setting, flag setting.

3.2.1 Password setting

After running the program, you can see the “Password setting” item in the toolbar. Press on that item, and the password setting dialog will pop up. It is shown as figure 4. You can modify the password there. Note that the initial password is 1234.



Figure 4

You can also see the “Download setting” item in the toolbar. Press on it and the log dialog will pop up as shown in Figure 5. Only after inputting the correct password, you will see that the download setting dialog will pop up.



Figure 5

3.2.2 Port setting

In the the port tab of the download setting, shown as the figure 6, you can set the port index, the COM to be used, the baud rate and the color identifier.




Figure 6

Parameter elucidation:

- * **Serial number:** The port which you selected by checking the check boxes is available.
- * **Serial port:** Set the serial port according to the figure 2.
- * **Baud rate:** The speed of data transfers suggested 921600.
- * **Display color:** Select the color according to the line color of the port to be easily identified.

3.2.3 Download info setting

In the download tab of the download setting(see figure 7), you can choose the program file used. We can download a .lod file or a .cfp file. The .lod file is the standard format file of the coolsand mobile. The .cfp file is a text file that contain the calibration parameters of our mobile phone. If an accessorial file is needed to be download along, select the corresponding checkbox and choose the path of that file.

If we want to download a .cfp file, then the “Update calibration parameters” radio buttons will became enabled. In which we can select to update the audio section or the RF section or the battery sections. Another thing, once we select to download a .cfp file, the accessorial functions like erasing sectors, writing flags ,writing SN etc. will be ignored.




Figure 7-1




Figure 7-2

3.2.4 Chip setting

In the ChipSet tab of the download setting, you can choose the chip type and the flash type used by the mobile, and the erase option. It's shown as Figure 8.

Setting chipset:

We can set the chip and the flash type used in our mobile phone, the user must truly set these parameters of the mobile phones which will be mass product. Or else a error of downloading will occur. If the user did not use the standard design provided by Coolsand , they also can select “Others” item in the “Platform” combobox, and click the “Browse>>” button to select a special flash programmer file (*_ramrun.lod) for the mobile phone.

Erase setting:

1. **Erase factory setting sector:** Erase the sector that hold the factory setting data before downloading.
2. **Erase calibration sector:** Erase the sector that hold the calibration data before downloading.
3. **Erase user data sector:** Erase the sector that hold the user's data before downloading.
4. **Erase full flash:** Erase the whole sectors before downloading.




Figure 8

3.2.5 Flag setting

In the Set flag tab of the download setting, you can choose the flag option. It's shown as figure 9.




Figure 9

Check last worksite flag: Check the complete flag of the last worksite on the product line. If the last worksite isn't finished, the operation of the current worksite can't begin. This option is always not selected, because it is often the first worksite for downloading.

Set current worksite flag: This option is selected if setting the finished flag of the current worksite is needed. And then choose the flag. The downloading is normally the first worksite, so we can select the "The 1st worksite".

Set power on mode flag: This option is selected if it needs to set the power on mode at the current worksite.

3.2.6 SN setting

In the write SN tab of the download setting, you can choose the related option of downloading SN. It's shown as figure 10.




Figure 10

Choose the Motherboard SN checkbox to set the related setting about MBSN:

- From data file is chosen to input the MBSN from a Excel file in which there must be a table called “MBSN” and the MBSN numbers are listed in the first column.
- If Custom number is chosen, you have to input the initial MBSN in the Initial number and designate the position to be generated automatically in the mask.
- Initial number and mask must match, and * represents the position to be generated automatically and these characters must be digital numbers from 0 to 9. Another thing, If we hope the MBSN contain the date in a given position, we can set the given position of the Initial number and mask to be “##%””, Then “##%” will be replaced by the month and day value when we write the MBSN to the mobile phone.
- Max limited number is used for From data file and Custom number. It means that you can’t add any MBSN when the total number of MBSN were created reached the limit number.

Choose the Phone SN checkbox to set the related setting about PSN:

- From data file is chosen to input the PSN from a Excel file in which there must be a table called PSN and the PSN numbers are listed in the first column.
- If Custom number is chosen, you have to input the initial PSN in the Initial number and designate the position to be generated automatically in the mask.
- Attention: Initial number and mask must match and * represents the position to be generated automatically, and these characters must be digital numbers from 0 to 9.
- Max limited number is used for data file mode and Custom mode. It means that you can’t add any PSN when the total number of PSN were created reached the limit number.

4 Run the download tool

4.1 Run the download tool

Click the icon to run download tool shown as figure 11.




Figure 11

4.2 Start downloading

Start all ports to download by clicking the corresponding item on the toolbar. And then all ports prepare to start the download process. Start single port by clicking the button at the back of each port. The progressbar is changed from hoar into white now, shown as the figure 12.




Figure 12

4.3 Connect to the cellular phone

Plug a cellular phone to the port, and then the port will find that the port connects the mobile successfully. The corresponding progressbar changes to aqua which means that it detects the phone successfully, shown as the figure 13.




Figure 13

4.4 Download the lod file

After detecting the mobile successfully, the program begins to download the lod file. A progressbar is shown to display the percentage of the download progress from 1% to 100% while the status will change from “Downloading” to “Finished”. The progress is shown in the figure 14 and 15




Figure 14




Figure 15

4.5 Start or stop the download process solely

If you hope to start or stop one port solely, you can right-click the mouse on the very row of the port, then you can find a popup menu like the below figure, In which there are 2 menu items “Start” and “stop”. Click them you can start or stop the very port solely.




Figure 16

4.6 Unplug the cellular phone

Unplug the cellular phone; waiting for the idle state (white) appearance, then put another cellular phone to the fixture.

Pay attention to:

1. The operator must wait until the former mobile has finished and the finish state is shown, and then he can unplug the phone.
2. The operator can plug a new phone only when the port is idle again (The progress bar turns to white) after unplugging the former one.
3. The tool will display the count of both successful and failed downloading. However, if press the button “Stop”, the count will be cleared to zero.

5 Troubleshooting

In the process of downloading, thanks to the hardware error or the operating error, the process may quit or stop occasionally. The user can use the eight groups of buttons(Start/Stop) to do the following steps:

1. Click the stop button of the port that encounter the error and stop downloading.
2. Unplug out the unfinished mobile.
3. Click the start button to restart the download process.
4. Plug the mobile in the fixture, start downloading.
5. If the above steps take no effect, please restart the Windows.